



[Knowledgebase](#) > [Power Management](#) > [easYgen-3000XT](#) > [communication](#) > [easYgen-3000XT with J1939 speed bias to ECU of FPT/IVECO model "MD1"](#)

easYgen-3000XT with J1939 speed bias to ECU of FPT/IVECO model "MD1"

Justin Schneider - 2026-07-27 - [communication](#)

ECU brand: FPT / IVECO

ECU model: MD1

Here speed bias through J1939 communication works only with easYgen-3000XT having version 2.12 or higher

easYgen-3000XT, with version **2.12** is prepared to have an additional ECU selection called "**Standard C**"

This does include the mandatory Checksum and Counter values for that kind of ECU.

(The J1939-Standard does not state the values as mandatory, but the MD1 actually does!!!)

1. Update your easYgen-3000XT to version equal or higher than >>2.12-1<<
Firmware files available here: <https://wss.woodward.com/manuals/Support/Forms/AllItems.aspx>
2. Set parameter at "Configure Application -> Configure Controller -> Frequency controller" as follows...

3. Set parameters at "Configure Interfaces -> CAN 2 -> J1939" as follows...

4. Finally re-boot the easYgen, see Parameter #10419 above.